



ENERGY TO MATCH YOURS.  
**POWER LOGIX**  
®

# HONDA 7000 GENERATOR

- **THE PERFECT BALANCE OF POWER AND LOGISTICS.**
- **INVERTER - STABLE POWER FOR COMPUTERS AND MORE.**
- **CONVENIENT ELECTRIC START.**
- **SUPER QUIET.**

At Deployed Logix we're redefining rapid deployment. Through our extensive work with law enforcement, search and rescue teams, various first responders, private organizations both domestically and abroad, and the military, our team understands that when a crisis calls, seconds count. Discover why we are the leader in American-made, rapidly deployable disaster preparedness products.

Specification and design may be altered without notice due to continuous product development. LAST UPDATED OCTOBER 2020

CAGE CODE: 7CFK2 DUNS#: 079751064  
Berry Amendment Compliant

# UNIT SPECIFICATION

<b>ENGINE:</b>	Honda GX390 EFI
<b>DISPLACEMENT:</b>	389 cc
<b>AC OUTPUT:</b>	120 / 240V, 7000 W max.(58.3 / 29.1 AMP) 5500 W rated (45.8 / 22.9 AMP)
<b>RECEPTACLES:</b>	(2) 20 AMP, 125V GFCI duplex, 30 AMP, 125V locking plug 30 AMP, 125 / 250V locking plug
<b>DC OUTPUT:</b>	NA
<b>STARTING SYSTEM:</b>	Recoil, electric
<b>FUEL TANK CAPACITY:</b>	5.1 gal. (20.4 L)
<b>RUN TIME PER TANKFUL:</b>	6.5 hr @ rated load, 18 hr @ 1/4 load
<b>DIMENSIONS:</b>	33.40 x 27.60 x 28.40 in (84.80 x 70.10 x 72.10 cm)
<b>NOISE LEVEL:</b>	58 dB (AMP) @ rated load, 52 dB (AMP) @ 1/4 load

